

Part No. 201201-B
October 1999

4401 Great America Parkway
Santa Clara, CA 95054

Getting Started with Optivity Campus 7.0.2 for HP OpenView Network Node Manager and Tivoli TME 10 NetView

NORTEL
NETWORKS™

Copyright © 1999 Nortel Networks

All rights reserved. Printed in the USA. October 1999.

The information in this document is subject to change without notice. The statements, configurations, technical data, and recommendations in this document are believed to be accurate and reliable, but are presented without express or implied warranty. Users must take full responsibility for their applications of any products specified in this document. The information in this document is proprietary to Nortel Networks NA Inc.

The software described in this document is furnished under a license agreement and may only be used in accordance with the terms of that license. A summary of the Software License is included in this document.

Trademarks

NORTEL NETWORKS is a trademark of Nortel Networks.

Bay Networks and Optivity are registered trademarks and Autotopology, Campus Command Center, and Expanded View, are trademarks of Nortel Networks.

Microsoft, Windows, and Windows NT are registered trademarks of Microsoft Corporation.

All other trademarks and registered trademarks are the property of their respective owners.

Restricted Rights Legend

Use, duplication, or disclosure by the United States Government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.227-7013.

Notwithstanding any other license agreement that may pertain to, or accompany the delivery of, this computer software, the rights of the United States Government regarding its use, reproduction, and disclosure are as set forth in the Commercial Computer Software-Restricted Rights clause at FAR 52.227-19.

Statement of Conditions

In the interest of improving internal design, operational function, and/or reliability, Nortel Networks NA Inc. reserves the right to make changes to the products described in this document without notice.

Nortel Networks NA Inc. does not assume any liability that may occur due to the use or application of the product(s) or circuit layout(s) described herein.

Portions of the code in this software product may be Copyright © 1988, Regents of the University of California. All rights reserved. Redistribution and use in source and binary forms of such portions are permitted, provided that the above copyright notice and this paragraph are duplicated in all such forms and that any documentation, advertising materials, and other materials related to such distribution and use acknowledge that such portions of the software were developed by the University of California, Berkeley. The name of the University may not be used to endorse or promote products derived from such portions of the software without specific prior written permission.

SUCH PORTIONS OF THE SOFTWARE ARE PROVIDED "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

In addition, the program and information contained herein are licensed only pursuant to a license agreement that contains restrictions on use and disclosure (that may incorporate by reference certain limitations and notices imposed by third parties).

Nortel Networks NA Inc. Optivity® Network Management Software License Agreement

NOTICE: Please carefully read this license agreement before copying or using the accompanying Optivity network management software or installing the hardware unit with pre-enabled Optivity network management software (each of which is referred to as “Software” in this Agreement). BY COPYING OR USING THE SOFTWARE, YOU ACCEPT ALL OF THE TERMS AND CONDITIONS OF THIS LICENSE AGREEMENT. THE TERMS EXPRESSED IN THIS AGREEMENT ARE THE ONLY TERMS UNDER WHICH NORTEL NETWORKS WILL PERMIT YOU TO USE THE SOFTWARE. If you do not accept these terms and conditions, return the product, unused and in the original shipping container, within 30 days of purchase to obtain a credit for the full purchase price.

1. License Grant. Nortel Networks NA Inc. (“Nortel Networks”) grants the end user of the Software (“Licensee”) a personal, nonexclusive license: a) to use the Software either on a single computer or, if applicable, on a single authorized device identified by host ID; b) to copy the Software solely for backup purposes in support of authorized use of the Software; and c) to use and copy the associated user manual solely in support of authorized use of the Software by Licensee. This license applies to the Software only and does not extend to Nortel Networks Agent software or other Nortel Networks software products. Nortel Networks Agent software or other Nortel Networks software products are licensed for use under the terms of the applicable Nortel Networks NA Inc. Software License Agreement that accompanies such software and upon payment by the end user of the applicable license fees for such software.

2. Restrictions on use; reservation of rights. The Software and user manuals are protected under copyright laws. Nortel Networks and/or its licensors retain all title and ownership in both the Software and user manuals, including any revisions made by Nortel Networks or its licensors. The copyright notice must be reproduced and included with any copy of any portion of the Software or user manuals. Licensee may not modify, translate, decompile, disassemble, use for any competitive analysis, reverse engineer, distribute, or create derivative works from the Software or user manuals or any copy, in whole or in part. Except as expressly provided in this Agreement, Licensee may not copy or transfer the Software or user manuals, in whole or in part. The Software and user manuals embody Nortel Networks’ and its licensors’ confidential and proprietary intellectual property. Licensee shall not disclose to any third party the Software, or any information about the operation, design, performance, or implementation of the Software and user manuals that is confidential to Nortel Networks and its licensors; however, Licensee may grant permission to its consultants, subcontractors, and agents to use the Software at Licensee’s facility, provided they have agreed to use the Software only in accordance with the terms of this license.

3. Limited warranty. Nortel Networks warrants each item of Software, as delivered by Nortel Networks and properly installed and operated on Nortel Networks hardware or other equipment it is originally licensed for, to function substantially as described in its accompanying user manual during its warranty period, which begins on the date Software is first shipped to Licensee. If any item of Software fails to so function during its warranty period, as the sole remedy Nortel Networks will at its discretion provide a suitable fix, patch, or workaround for the problem that may be included in a future Software release. Nortel Networks further warrants to Licensee that the media on which the Software is provided will be free from defects in materials and workmanship under normal use for a period of 90 days from the date the Software is first shipped to Licensee. Nortel Networks will replace defective media at no charge if it is returned to Nortel Networks during the warranty period along with proof of the date of shipment. This warranty does not apply if the media has been damaged as a result of accident, misuse, or abuse. The Licensee assumes all responsibility for selection of the Software to achieve Licensee’s intended results and for the installation, use, and results obtained from the Software. Nortel Networks does not warrant a) that the functions contained in the software will meet the Licensee’s requirements, b) that the Software will operate in the hardware or software combinations that the Licensee may select, c) that the operation of the Software will be uninterrupted or error free, or d) that all defects in the operation of the Software will be corrected. Nortel Networks is not obligated to remedy any Software defect that cannot be reproduced with the latest Software release. These warranties do not apply to the Software if it has been (i) altered, except by Nortel Networks or in accordance with its instructions; (ii) used in conjunction with another vendor’s product, resulting in the defect; or (iii) damaged by improper environment, abuse, misuse, accident, or negligence. **THE FOREGOING WARRANTIES AND LIMITATIONS ARE EXCLUSIVE REMEDIES AND ARE IN LIEU OF ALL OTHER WARRANTIES EXPRESS OR IMPLIED, INCLUDING WITHOUT LIMITATION ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.** Licensee is responsible for the security of its own data and information and for maintaining adequate procedures apart from the Software to reconstruct lost or altered files, data, or programs.

4. Limitation of liability. IN NO EVENT WILL NORTEL NETWORKS OR ITS LICENSORS BE LIABLE FOR ANY COST OF SUBSTITUTE PROCUREMENT; SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES; OR ANY DAMAGES RESULTING FROM INACCURATE OR LOST DATA OR LOSS OF USE OR PROFITS ARISING OUT OF OR IN CONNECTION WITH THE PERFORMANCE OF THE SOFTWARE. EVEN IF NORTEL NETWORKS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN NO EVENT SHALL THE LIABILITY OF NORTEL NETWORKS RELATING TO THE SOFTWARE OR THIS AGREEMENT EXCEED THE PRICE PAID TO NORTEL NETWORKS FOR THE SOFTWARE LICENSE.

5. Government Licensees. This provision applies to all Software and documentation acquired directly or indirectly by or on behalf of the United States Government. The Software and documentation are commercial products, licensed on the open market at market prices, and were developed entirely at private expense and without the use of any U.S. Government funds. The license to the U.S. Government is granted only with restricted rights, and use, duplication, or disclosure by the U.S. Government is subject to the restrictions set forth in subparagraph (c)(1) of the Commercial Computer Software—Restricted Rights clause of FAR 52.227-19 and the limitations set out in this license for civilian agencies, and subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause of DFARS 252.227-7013, for agencies of the Department of Defense or their successors, whichever is applicable.

6. Use of Software in the European Community. This provision applies to all Software acquired for use within the European Community. If Licensee uses the Software within a country in the European Community, the Software Directive enacted by the Council of European Communities Directive dated 14 May, 1991, will apply to the examination of the Software to facilitate interoperability. Licensee agrees to notify Nortel Networks of any such intended examination of the Software and may procure support and assistance from Nortel Networks.

7. Term and termination. This license is effective until terminated; however, all of the restrictions with respect to Nortel Networks' copyright in the Software and user manuals will cease being effective at the date of expiration of the Nortel Networks copyright; those restrictions relating to use and disclosure of Nortel Networks' confidential information shall continue in effect. Licensee may terminate this license at any time. The license will automatically terminate if Licensee fails to comply with any of the terms and conditions of the license. Upon termination for any reason, Licensee will immediately destroy or return to Nortel Networks the Software, user manuals, and all copies. Nortel Networks is not liable to Licensee for damages in any form solely by reason of the termination of this license.

8. Export and Re-export. Licensee agrees not to export, directly or indirectly, the Software or related technical data or information without first obtaining any required export licenses or other governmental approvals. Without limiting the foregoing, Licensee, on behalf of itself and its subsidiaries and affiliates, agrees that it will not, without first obtaining all export licenses and approvals required by the U.S. Government: (i) export, re-export, transfer, or divert any such Software or technical data, or any direct product thereof, to any country to which such exports or re-exports are restricted or embargoed under United States export control laws and regulations, or to any national or resident of such restricted or embargoed countries; or (ii) provide the Software or related technical data or information to any military end user or for any military end use, including the design, development, or production of any chemical, nuclear, or biological weapons.

9. General. If any provision of this Agreement is held to be invalid or unenforceable by a court of competent jurisdiction, the remainder of the provisions of this Agreement shall remain in full force and effect. This Agreement will be governed by the laws of the state of California.

Should you have any questions concerning this Agreement, contact Nortel Networks, 4401 Great America Parkway, P.O. Box 58185, Santa Clara, California 95054-8185.

LICENSEE ACKNOWLEDGES THAT LICENSEE HAS READ THIS AGREEMENT, UNDERSTANDS IT, AND AGREES TO BE BOUND BY ITS TERMS AND CONDITIONS. LICENSEE FURTHER AGREES THAT THIS AGREEMENT IS THE ENTIRE AND EXCLUSIVE AGREEMENT BETWEEN NORTEL NETWORKS AND LICENSEE, WHICH SUPERSEDES ALL PRIOR ORAL AND WRITTEN AGREEMENTS AND COMMUNICATIONS BETWEEN THE PARTIES PERTAINING TO THE SUBJECT MATTER OF THIS AGREEMENT. NO DIFFERENT OR ADDITIONAL TERMS WILL BE ENFORCEABLE AGAINST NORTEL NETWORKS UNLESS NORTEL NETWORKS GIVES ITS EXPRESS WRITTEN CONSENT, INCLUDING AN EXPRESS WAIVER OF THE TERMS OF THIS AGREEMENT.

Contents

Preface

Before You Begin	xi
Audience	xii
Text Conventions	xii
Related Publications	xiii
How to Get Help	xiv

Chapter 1

Preparing for Installation

Network Environment	1-2
System Requirements	1-2
Supported Agents	1-3
Internetworking Module Requirements	1-4
Filtering Segment Hellos for Autotopology	1-4
Filtering Flat Network Hellos	1-5
Network Information Requirements	1-6
Network Information Checklist	1-7

Chapter 2

Installing Optivity Campus

Running the Setup Program	2-2
Upgrading Optivity Campus	2-8
Uninstalling Optivity Campus	2-9
Troubleshooting Information	2-10
Using Static Versus Dynamic IP Addresses	2-10
Verifying Connectivity	2-10

Chapter 3

Postinstallation Tasks

Understanding Windows Environment Changes	3-1
Backing Up Database Files	3-2

Chapter 4

Getting Started with Optivity Campus

Starting Optivity Campus	4-1
Discovering Network Devices	4-3
Choosing a Discovery Seed Router	4-4
Specifying Community Strings	4-5
Running Autodiscovery	4-8
Using IP Discovery	4-9
Using IPX Discovery	4-17
Scheduling Discovery	4-18
Saving a Campus Command Center View	4-20
Running Optivity Node Discovery	4-21
Setting Optivity System Preferences	4-21
Changing Campus Command Center Preferences	4-22
Changing NMS Configuration	4-23
Using Optivity Campus Applications	4-24

Index

Figures

Figure 1-1.	Model 332XS Forwarding Table	1-5
Figure 2-1.	Network Management Platform Selection Dialog Box	2-3
Figure 2-2.	Optivity Campus Setup Components Dialog Box (HP OpenView Network Node Manager	2-4
Figure 2-3.	Communications Setup Dialog Box	2-6
Figure 4-1.	Campus Command Center Window with the Autodiscovery Dialog Box ..	4-2
Figure 4-2.	Autodiscovery Dialog Box—Seed Router Section	4-4
Figure 4-3.	System Properties Dialog Box—Community Strings Tab	4-7
Figure 4-4.	Autodiscovery Dialog Box—IP Discovery Tab	4-10
Figure 4-5.	Autodiscovery Dialog Box—Router Discovery	4-12
Figure 4-6.	Autodiscovery Dialog Box—ARP Cache Discovery	4-14
Figure 4-7.	Autodiscovery Dialog Box—Range PINGing Discovery	4-16
Figure 4-8.	Autodiscovery Dialog Box— IPX Discovery Tab	4-17
Figure 4-9.	Autodiscovery Dialog Box—Scheduler Tab	4-19
Figure 4-10.	System Properties Dialog Box—Command Center Tab	4-22
Figure 4-11.	System Properties Dialog Box—NMS Configuration Tab	4-23

Tables

Table 1-1.	Optivity Campus 7.0.2 System Requirements	1-2
Table 2-1.	Optivity Files Saved During Upgrade	2-8
Table 3-1.	Environment Settings	3-1
Table 4-1.	Optivity Campus Discovery Types	4-3
Table 4-2.	IP Discovery Methods	4-9

Preface

Welcome to Optivity® Campus, a graphical network management application for midsize to large campus network environments. Optivity Campus provides an Autodiscovery feature that automatically discovers and displays all subnetworks, hubs, bridges, probes, switches, routers, and servers to create a blueprint of your network configuration. Optivity also delivers advanced management for multi-LAN, Ethernet, and token ring networks. Optivity Campus runs under both Microsoft® Windows NT®, and Windows 95® and integrates with HP OpenView Workgroup Node Manager (WNM), HP OpenView Network Node Manager (NNM), or Tivoli TME 10 NetView Windows-based network management platforms for Windows.

This preface describes the contents of this guide and provides information about how to use it along with the other publications included with your Optivity Campus software.

Nortel Networks recommends that you read this document before getting started with Optivity Campus network management application.

Before You Begin

This guide describes how to install Optivity Campus to integrate with HP OpenView Network Node Manager and Tivoli TME 10 NetView on your management station. It also describes how to set up Optivity Campus for optimal performance. Additionally, it describes how to get started using Optivity Campus to proactively manage your network.

This guide covers using Optivity Campus only. For information on using your management station, Windows 95, Windows NT, HP OpenView Network Node Manager, and Tivoli TME 10 NetView, refer to the documentation included with those products.

For detailed information about how to use Optivity Campus, refer to *Using Optivity Campus 7.0* (located on the Optivity Campus 7.0.2 Documentation CD).

Audience

This guide is intended for Ethernet and token ring local area network (LAN) administrators with the following background:

- Working knowledge of IBM PC terminology and operation
- Working knowledge of Microsoft Windows NT
- Familiarity with the IP and IPX protocols
- Familiarity with either HP OpenView Network Node Manager or Tivoli TME 10 NetView

Text Conventions

This guide uses the following text conventions:

angle brackets (<>) Indicate that you choose the text to enter based on the description inside the brackets. Do not type the brackets when entering the command.

Example: If the command syntax is:

ping <ip_address>, you enter:

ping 192.32.10.12

bold text Indicates command names and options and text that you need to enter.

Example: Enter **show ip {alerts | routes}**.

Example: Use the **dinfo** command.

brackets ([]) Indicate optional elements in syntax descriptions. Do not type the brackets when entering the command.

Example: If the command syntax is:

show ip interfaces [-alerts], you can enter either:

show ip interfaces or **show ip interfaces -alerts**.

<i>italic text</i>	Indicates file and directory names, new terms, book titles, and variables in command syntax descriptions. Where a variable is two or more words, the words are connected by an underscore. Example: If the command syntax is: show at <valid_route> valid_route is one variable and you substitute one value for it.
screen text	Indicates system output, for example, prompts and system messages. Example: Set Trap Monitor Filters
separator (>)	Shows menu paths. Example: Protocols > IP identifies the IP option on the Protocols menu.

Related Publications

For more information about using Optivity Campus, refer to one or more of the following publications:

- *Getting Started with Optivity Campus 7.0.2 for HP OpenView Workgroup Node Manager*
(Bay Networks® part number 893-660-H)

Provides instructions essential to software installation and is designed for the experienced user.
- *Using Optivity Campus 7.0*
(Bay Networks part number 893-786-E)

Provides complete instructions for using the Optivity Campus integrated applications to manage, monitor, and configure your network. This document is located on the *Optivity Campus 7.0.2 Documentation* CD. To use the CD, see [page 4-24](#).
- *Release Notes for Optivity Campus 7.0.2*
(Bay Networks part number 896-007-L)

Provides up-to-date information about this Optivity Campus release.

You can print selected technical manuals and release notes free, directly from the Internet. Go to support.baynetworks.com/library/tpubs/. Find the product for which you need documentation. Then locate the specific category and model or version for your hardware or software product. Using Adobe Acrobat Reader, you can open the manuals and release notes, search for the sections you need, and print them on most standard printers. You can download Acrobat Reader free from the Adobe Systems Web site, www.adobe.com.

You can purchase selected documentation sets, CDs, and technical publications through the collateral catalog. The catalog is located on the World Wide Web at support.baynetworks.com/catalog.html and is divided into sections arranged alphabetically:

- The “CD ROMs” section lists available CDs.
- The “Guides/Books” section lists books on technical topics.
- The “Technical Manuals” section lists available printed documentation sets.

How to Get Help

If you purchased a service contract for your Nortel Networks product from a distributor or authorized reseller, contact the technical support staff for that distributor or reseller for assistance.

If you purchased a Nortel Networks service program, contact one of the following Nortel Networks Technical Solutions Centers:

Technical Solutions Center	Telephone Number
Billerica, MA	800-2LANWAN (800-252-6926)
Santa Clara, CA	800-2LANWAN (800-252-6926)
Valbonne, France	33-4-92-96-69-68
Sydney, Australia	61-2-9927-8800
Tokyo, Japan	81-3-5402-7041

Chapter 1

Preparing for Installation

This chapter provides information you need to know before installing Optivity Campus to run with HP OpenView Network Node Manager or Tivoli TME 10 NetView.

Optivity Campus is a graphical network management application that integrates with HP OpenView Network Node Manager and Tivoli TME 10 NetView network management platforms, allowing you to manage and monitor devices on Ethernet and token ring networks. You will need to purchase and install these network management platforms separately.

For more information on Optivity Campus features, see Chapter 1, “Overview,” of *Using Optivity Campus 7.0* (located on the *Optivity Campus 7.0.2 Documentation CD*).

Network Environment

Optivity Campus with HP OpenView Network Node Manager or Tivoli TME 10 NetView installed on your management station allows you to manage multi-LAN, Ethernet and token ring network segments that consist of supported Nortel Networks internetworking devices and agents.

System Requirements

Before you install Optivity Campus 7.0.2 with HP OpenView Network Node Manager or Tivoli TME 10 NetView for Windows, ensure that the network management station(s) upon which you install software meets the requirements defined in [Table 1-1](#).

Table 1-1. Optivity Campus 7.0.2 System Requirements

Description	Requirement
Management Station	Pentium IBM-compatible PC operating at 333 MHz recommended, 166 MHz minimum
RAM	128 MB recommended, 32 MB minimum
Disk Space	125 MB for Optivity Campus 7.0.2 recommended, 111 minimum
Swap Space (Virtual Memory)	70 MB for NNM; 128 MB for NetView
Video Adapter	VGA or Super VGA adapter and display
Operating Environment	<ul style="list-style-type: none"> • Microsoft Windows 95 • Windows NT 4.0 with Service Pack 4 or 5
Communications Stack	<ul style="list-style-type: none"> • Winsock implementation on Microsoft TCP/IP stack. • IPX stack is supported only under Windows 95.
Network Management Platform	<ul style="list-style-type: none"> • HP OpenView Network Node Manager 6.0 for Windows NT 4.0 • Tivoli TME 10 NetView 5.1 for Windows NT 4.0
CD-ROM Drive	8 X recommended, 2 X minimum
Mouse	Microsoft Windows-compatible

In addition to the software requirements already stated, please note the following:

- Optivity Campus 7.0.2 uses the Windows NT built-in TCP/IP stack. When installing, make sure your system is fully configured and all network communications protocols are installed and running prior to installation.
- The Optivity Campus installation program saves backup copies of your *system.ini* files in the *c:\opt\saved* directory.

Supported Agents

Optivity Campus manages devices on Ethernet and token ring networks using the Simple Network Management Protocol (SNMP). The SNMP agent software either resides in the Bay Networks network management module (NMM) firmware, or is downloaded to the NMM from the management station, or is downloaded through the service port on the NMM. The agent software enables SNMP communication between individual internetworking devices and Optivity Campus.

Optivity Campus supports three types of agent software—Standard, Advanced, or Advanced Analyzer:

- Standard agents provide activity and diagnostic information down to a per-port level; they support a subset of the Optivity Campus features including Expanded View™.
- Advanced agents provide a mid-level feature set—these agents make Optivity Campus Autotopology™ possible and provide higher-level information. Advanced agents also provide partial RMON support, the Find Nodes and Show Nodes functions, and threshold creation on core statistics.
- Advanced Analyzer agents provide the richest feature set—by providing full RMON support and Super RMON support for collecting statistics.

For more information about agent software, see the documentation that came with your NMM hardware.

For information about downloading agents, see Chapter 10, “Booting New Devices and Maintaining Agents,” in *Using Optivity Campus 7.0* (located on the *Optivity Campus 7.0.2 Documentation CD*).

Internetworking Module Requirements

You can poll and manage third-party routers or bridges that offer SNMP-compliant software or provide standard Telnet access for status from the Optivity Campus management station using the Telnet application.

Filtering Segment Hellos for Autotopology

Configure all Ethernet bridges with the segment multicast address (the segment hello) in their filtering tables. The segment hello allows the Autotopology feature to operate properly. Token ring bridges need no filters. The segment hello disposition mode must be set to discard, to ensure a correct representation of your network topology. The following is an example:

```
010081000101
```

Hubs exchange segment hellos as well as flat network hellos. For more information about flat network hellos, see [“Filtering Flat Network Hellos”](#) on [page 1-5](#). When building network views using the Autotopology feature, Optivity Campus locates bridges and identifies network segments as a result of the bridge’s filtering the segment hello address.

If the bridge does not have this address in its filtering table, Optivity Campus cannot accurately depict the segment and bridge bounds.

[Figure 1-1](#) shows an example of the Model 332XS high-speed bridge forwarding table. The segment hello is a static entry; that is, it is made manually and not changed by Optivity Campus during the Autodiscovery process.

TB Address Database				Page 1 of 2	
Address	Dispn	Address	Dispn	Address	Dispn
* 02608C4BEC40	LAN B	* 08002002467E	LAN B	* 02608C4A5521	LAN B
* 02608C423348	LAN B	* 02608C579979	LAN B	* 0000C0BFEA06	LAN B
080090016241	LAN B	* 02608C4BD242	LAN B	02608C325804	LAN B
02608C704032	LAN B	0000C0EFA116	LAN B	0000C048831A	LAN B
* 0000C08BE918	LAN B	80001003FEFE	LAN B	0000C0B7FF18	LAN B
0000C0CB3614	LAN B	0000C0F5FB06	LAN B	* 0000C019041A	LAN B
* 0207010061B1	LAN B	800010030000	LAN B	0000C0D9A216	LAN B
0000C0291307	LAN B	0000C0362A19	LAN B	0000C0512114	LAN B
0000C0869E16	LAN B	02608C688641	LAN B	0000C059FE12	LAN B
0000C06BA216	LAN B	0000C01E1913	LAN B	08002B06209E	LAN B
0000C095071C	LAN B	0000C08C9C16	LAN B	0000C025A116	LAN B
080077002662	LAN B	020701039B4E	LAN B	+ 010081000101	Discard

Exit Next Page Prev Page Edit Table Search Item Go Page

* Unlearned + Static Total Entries= 52 Static Entries= 3
 Use cursor keys to choose option. Press <RETURN> to select.
 Press <CTRL> <P> to return to Main Menu.

Figure 1-1. Model 332XS Forwarding Table

As with all other network devices, before you can manage the Model 332XS bridge using Optivity Campus, enter its IP address, subnet mask, and SNMP community string. See the documentation included with your bridge for instructions on how to update its configuration and filtering tables.

Filtering Flat Network Hellos

Unless a router is configured for bridging, you do not need to alter router configuration to work with Optivity Campus. The exception is to update its address database for correct Bootstrap Protocol (BootP) server operation. From there, you can manage the bridge using Telnet and Optivity Campus to report status changes via color indicators.

For routers functioning as local bridges and remote bridges, add either or both the segment and flat network multicast address. Your entries depend on how you want the device represented in network topology. If you add only the segment multicast address, Optivity Campus considers the device to be a bridge. The following addresses are examples:

Segment multicast address	010081000101
Flat network multicast address	010081000100

If you have a BootP server on the network and booting requests have to pass through a router (for example, the management station has boot files for modules located on the other side of that router), configure the router address database so that network devices can boot properly. You must update the router database with the IP address of your Optivity Campus management station.

For more information, see the documentation that came with your bridge or router and Chapter 10, “Booting New Devices and Maintaining Agents,” in *Using Optivity Campus 7.0* (located on the *Optivity Campus 7.0.2 Documentation CD*).

Network Information Requirements

To set up network communications, you need the following information before beginning the installation procedure:

- IP address of your Optivity Campus management station. The IP address should be in standard dotted-decimal notation (x.x.x.x) and should fit the networking requirements for your network.
- IP addresses for NMMs, managed concentrators, bridges, routers, and any other SNMP/IP-based network device(s) that you want to be able to access from the Optivity Campus management station. If you are not using Optivity Campus to manage a device, you still need IP addresses to use the Ping or Telnet access options.
- Subnet masks being used in your network.

- SNMP community strings (read-only and read/write) for all devices you want to manage. The read-only string must match for all devices or they cannot be recognized during the Autotopology process. You can also use the read community strings to define domains in your network.
- Filtering on appropriate bridges is required for proper dynamic network views. See your bridge or router manuals for more information about filtering.

See the management guides provided with your device modules for instructions on assigning these values.

Network Information Checklist

Before proceeding with the installation, fill in the following information in the space below:

Default Gateway IP address	
Default Gateway subnet mask	
Default Gateway read community string	
IP address for management station	
Local subnet read community string	
Commonly used read community strings	

Chapter 2

Installing Optivity Campus

This chapter describes how to install Optivity Campus 7.0.2 to run from within HP OpenView Network Node Manager (NNM) and Tivoli TME 10 NetView network management platforms. Additionally, this chapter describes how to upgrade Optivity Campus and how to uninstall it if necessary.

Before installing Optivity Campus, ensure that your management station meets the system requirements defined on [page 1-2](#).

It is assumed that you have already installed either HP OpenView Network Node Manager or Tivoli TME 10 NetView network management platform on your management station. If you have not, please do so before proceeding with the Optivity Campus installation. For information about how to install Optivity Campus with HP OpenView Workgroup Node Manager, see *Getting Started with Optivity Campus 7.0.2 for HP OpenView Workgroup Node Manager*.

This chapter includes the following information:

- [“Running the Setup Program” on page 2-2](#)
- [“Upgrading Optivity Campus” on page 2-8](#)
- [“Uninstalling Optivity Campus” on page 2-9](#)
- [“Troubleshooting Information” on page 2-10](#)

Running the Setup Program

This section describes how to install Optivity Campus using the Setup program.

The Optivity Campus Setup program does the following:

- Lets you select the network management platform with which you want Optivity Campus to integrate
- Lets you enter your name and company name for device agent software upgrades
- Lets you specify the Optivity Campus components you want the Setup program to install and lets you select the destination directory
- Copies the Optivity files to your network management station and configures them
- Lets you specify the communications settings for your network, including IP address, read community strings, gateway IP address, and subnet mask
- Updates your system files

To install Optivity Campus:

- 1. Start Microsoft Windows on your management station.**
- 2. On Windows NT, log into the Windows NT workstation as a user with Administrator privileges.**
- 3. If the network management platform is running, exit it.**
- 4. Start the Optivity Campus Setup program.**

- a. Insert the *Optivity Campus 7.0.2 Software* CD into the CD-ROM drive.**

If Autorun is enabled, the Optivity Campus Setup program starts automatically. If Autorun is disabled, manually start the setup program as follows:

- b. Choose Start > Run.**

The Run dialog box opens.

- c. Type the following line in the Command Line field:**

[CDROM_drive]:setup\setup.exe

- d. Click OK.**

The Network Management Platform Selection dialog box opens.
([Figure 2-1](#)).




Figure 2-1. Network Management Platform Selection Dialog Box

5. **Select the network management platform that you have installed on your management station.**
6. **Click Next.**

The Setup program confirms whether or not you are logged in as Administrator (or an equivalent user) on the Windows NT machine, and that you have closed all NetView or Network Node Manager windows.

7. **Click Yes or No.**

If you click Yes, Optivity Setup prompts you for your name and your company name. If you click No, you must exit the Optivity Campus Setup program, close all windows, and thereafter rerun the Setup program.

8. **Enter your name and your company name.**

The company name should be the same name you used to register for Nortel Networks Support Services.

9. **Click Next.**

10. Choose the destination folder into which you want to install Optivity Campus 7.0.2.

11. Click Next.

The Optivity Campus Setup Components dialog box opens ([Figure 2-2](#)).




Figure 2-2. Optivity Campus Setup Components Dialog Box (HP OpenView Network Node Manager)

The Optivity Campus Setup Components dialog box for Tivoli TME 10 NetView is similar, and therefore is not shown.

12. Select the components that you want the Setup program to install.

- NNM Registration Files—The HP OpenView registration files.
- Optivity Campus—The Optivity Campus 7.0.2 application files.
- Misc—Various unsupported Optivity Campus applications.

By default all of the components are selected. If you are upgrading Optivity Campus, you may only want to select certain components.

If you want to change the destination directory for a component, select that component, click Change, and then change it.

The default destination directory for NNM registration files and bitmaps is *c:\NNM\registration*. The default destination directory for the Optivity Campus application files is *c:\opt*. The default destination directory for miscellaneous files is *c:\opt\unsupported*.

13. Click Next.

The Setup program copies the files to your network management station. Thereafter, the Communications Setup Dialog Box opens ([Figure 2-3](#)).

If the installation did not complete successfully, copy the files in the *c:\opt\saved* and *c:\<platform>\saved* directories to another directory before running the Setup program again.

When you run the Setup program again, database files that were not copied to the *saved* directory are overwritten.



The image shows a Windows-style dialog box titled "Communications Setup". It is divided into three sections. The first section, "Please enter the following information about your seed router:", contains three input fields: "Discovery Seed Router IP Address" with the value "10.127.2.1", "Subnet Mask" with "255.255.255.0", and "Read Community String" with "public". The second section, "Please enter the following information about your network management station:", contains two input fields: "Network Management Station IP Address" with "134.177.125.100" and "Local Subnet Read Community String" with "public". The third section, "Commonly Used Read Community Strings:", features a list box containing "citation", "commuter", "private", "public", and "stationair", with "Add" and "Delete" buttons to its right. At the bottom of the dialog are "OK" and "Cancel" buttons.

Figure 2-3. Communications Setup Dialog Box

The Discovery Seed Router IP Address, IP Address, and Subnet Mask fields are already filled in with your management station and network settings.



Note: Optivity Campus retrieves information from your IP stack configuration settings. It defaults to using your default gateway router as your discovery seed router. If you wish to specify a different seed router, you can do so now or alternatively, you can specify a different discovery seed router after installation using the Optivity Campus Autodiscovery dialog box (see [page 4-8](#)) or the System Preferences dialog box (see [page 4-23](#)).

14. Check that your network information is correct, and enter the read community string for the seed router and your local subnet.

In the Commonly Used Read Community Strings text box, enter each string and click Add. Repeat this procedure until you have added all strings in the list box.



Note: You can also enter gateway and community string information after the installation using the Optivity System Properties dialog box. To reach that dialog box, choose Start > Programs > Optivity for HP OpenView > Optivity System Preferences.

15. Click Next.

The Setup program notifies you that it has modified your network management platform files and has placed them and copies of files from previous Optivity Campus installations in *c:\opt\saved*.

16. Click OK.

The Setup Complete dialog box opens and prompts you to restart your computer for system modifications to take effect.

17. Click Yes to restart your computer immediately, or click No if you want to wait before restarting the computer.

18. Click Finish to exit the Setup program.

19. Verify that the Start > Programs > Optivity for HP OpenView submenu exists.

Nortel Networks recommends that you read the next chapter before starting to use Optivity Campus.

Upgrading Optivity Campus

This section describes how to upgrade Optivity Campus to run from within HP OpenView Network Node Manager and Tivoli TME 10 NetView. You can upgrade Optivity Campus from versions 7.0 and 7.0.1.

To upgrade Optivity Campus:

1. **Start Windows and log in as Administrator.**
2. **Close all other programs.**
3. **Install Optivity Campus as described on [page 2-2](#).**

When you upgrade Optivity Campus from a previous version, the Setup program automatically saves many of the important files used by the previous installation. All files are saved to the `\opt\saved` directory.

[Table 2-1](#) lists these files.

Table 2-1. Optivity Files Saved During Upgrade

Files	File name Extension	Default Path
Optivity database	.d*, .k*	c:\opt\db\
Community string files	comstr.ini, descdb.ini	c:\opt\bin
Image files	.img	c:\opt\images\
Configuration files	.cfg	c:\opt\images\ or c:\opt\profile\
Campus Command Center Configuration files	<viewname>.ccc,	c:\opt\bin\
Optivity .ini files	constr.ini, synopt.ini, thlddata.ini, thldplt.ini	c:\opt\bin

4. **After upgrading Optivity Campus, copy the saved files back to their original locations in the `\opt` directory structure.**
5. **Restart your management station.**

Uninstalling Optivity Campus

This section describes how to uninstall Optivity Campus from your management station.

During the Optivity installation, all of the system configuration files modified by the setup program, such as *win.ini*, are saved to the *c:\opt\saved* directory. Also, platform files modified by the setup program are saved to a *\saved* subdirectory of the directory where the platform software is installed. The Setup program then modifies new versions of these files during the installation process.



Note: It is not necessary to modify the *win.ini* file if you will reinstall Optivity Campus at a later date. However, if you want to permanently uninstall Optivity Campus, remove the following sections from the *win.ini* file:

```
[Optivity]
[Optivity for OpenView]
[BPTFTP]
[Synoptics Generic Apps]
[OpenView]
```

To uninstall Optivity Campus:

1. **Restore the files in the *\saved* directories to their original locations.**
-



Note: The system files in the *c:\opt\saved* directories may not be current if you installed other software packages after the Optivity Campus installation.

2. **Delete the Optivity Campus files.**

The default directory is *c:\opt*. You can right-click the default directory and select Delete from the shortcut menu, or you can do the following:

- a. **Use Windows Explorer or choose Start > Programs > Command Prompt.**

The Command Prompt window opens.

- b. **At the command prompt, type:**

```
rmdir /s /q c:\opt\
```

3. **Restart your management station.**

Troubleshooting Information

Using Static Versus Dynamic IP Addresses

Optivity Campus does not support Dynamic Host Configuration Protocol (DHCP). The IP address, subnet mask, and default gateway address settings for Optivity Campus are obtained only once during the Setup process and are pulled from the TCP/IP setting of the Microsoft TCP/IP communications stack. The Optivity Campus management station must maintain a static IP address for the purpose of being reachable as an IP Trap receiver and BootP server.

Verifying Connectivity

Use Ping to verify the presence of any local IP address or your default router or gateway.

To run Ping:

- At the command prompt, type:
ping <IP_Address_of_device_that_you_want_to_verify_connectivity>

If the Ping fails, you may have specified an illegal IP address, default gateway, or subnet mask.



Note: If you ever change the network settings subsequent to installation, change the network settings in Optivity Campus by choosing Start > Optivity > Optivity System Preferences. The Optivity System Preferences dialog box opens. Make the network setting changes on the NMS Configuration tab of the Optivity System Preferences dialog box. You can also perform network setting changes by modifying the [Optivity] section in the *c:\opt\bin\synopt.ini* file.

Chapter 3

Postinstallation Tasks

This chapter describes the tasks that you should perform after you have installed the Optivity Campus software and before you use it.

This chapter includes the following information:

- [“Understanding Windows Environment Changes,”](#) next
- [“Backing Up Database Files” on page 3-2](#)

Understanding Windows Environment Changes

This section describes changes made to your Windows environment to optimize performance and ensure system stability.

[Table 3-1](#) describes the changes and additions to the system environment that are made by the Optivity Campus Setup program during installation to your management station environment settings.

Table 3-1. Environment Settings

Added Settings	Description
ARMONHOME =C:\OPT\ARMON PATH=C:\OPT\ARMON\AR_QFC;%PATH% PATH=C:\OPT\BIN;%PATH%	Verify that the paths to the Optivity and platform directories have been added.
PATH=C:\OPENVIEW\BIN	OpenView NNM only
PATH=C:\USR\OV\BIN	NetView only

Backing Up Database Files

This section describes how to back up your database files:

- To save your map and its associated database files, save and restore the following files to the appropriate directory:

`C:\OPT\DB\TOPODB.*` (includes .D1-D6, .K1-K5, .DBD)

`C:\OPT\DB\DCSDB.*` (includes .D1-D7, .K1, .DBD)

- To restore the database, enter the following commands:

cd c:\opt\db

erase *.*

restore <backup directory> c:

- To ensure proper system operation, periodically back up these files:

`c:\opt\images\bptftp.out` (Saved BootP/TFTP log)

`c:\opt\bin*.fnn` (Saved Flat Network View maps)

`c:\opt\bin*.sgv` (Saved Segment View maps)

Chapter 4

Getting Started with Optivity Campus

This chapter describes how to start Optivity Campus from within HP OpenView Network Node Manager or Tivoli TME 10 NetView. It describes how to discover network devices using Autodiscovery. Additionally, it describes how to set Optivity Campus system properties.

It is recommended that you read this chapter before you use the Optivity Campus network management and monitoring features described in *Using Optivity Campus 7.0* (located on the *Optivity Campus 7.0.2 Documentation CD*).

This chapter includes the following information:

- [“Starting Optivity Campus,”](#) next
- [“Discovering Network Devices” on page 4-3](#)
- [“Setting Optivity System Preferences” on page 4-21](#)
- [“Using Optivity Campus Applications” on page 4-24](#)

Starting Optivity Campus

This section describes how to start Optivity Campus from within HP OpenView Network Node Manager and Tivoli TME 10 NetView.

To start Optivity Campus:

1. Start Network Node Manager or NetView.

- To start Network Node Manager, choose Start > Programs > HP OpenView > Network Node Manager.
- To start NetView, choose Start > Programs > NetView > NetView Console.

2. In NetView or NNM, choose Applications > Optivity.

The first time you start Optivity Campus, the Campus Command Center™ window opens (Figure 4-1), and it is blank. The Autodiscovery dialog box opens blank on top of the Campus Command Center window. Additionally, several Optivity Campus processes start and display minimized in the Windows taskbar.




Figure 4-1. Campus Command Center Window with the Autodiscovery Dialog Box

The Campus Command Center provides a graphical representation of your campus network resources. You can use the Optivity Campus Autodiscovery feature to locate devices within your network and thus populate the appropriate Campus Command Center folders.

Discovering Network Devices

Before you can use Optivity Campus to monitor and manage your network, you must run the discovery features to locate and identify the devices connected to your network.

Discovering network devices involves these tasks:

- Running the Campus Command Center Autodiscovery process
- Running the Optivity Node Discovery process

The Campus Command Center Autodiscovery feature is independent from Optivity Node Discovery.

The two discovery types are summarized in [Table 4-1](#).

Table 4-1. Optivity Campus Discovery Types

Discovery Type	Description	When to Run
Campus Command Center Autodiscovery	Discovers Nortel Networks specific devices so that they can appear in Campus Command Center folders and Optivity Campus displays. Device information is stored in the Optivity device database.	After Platform Discovery
Optivity Node Discovery	Discovers network nodes by getting Show Nodes information from Nortel Networks devices that have Advanced agent software. The node information is added to the Optivity device database.	After Campus Command Center Autodiscovery

Choosing a Discovery Seed Router

Before you run the Optivity Campus Autodiscovery, you need to specify a seed router. You should specify a seed router that is on or near the subnet or subnets that you are most interested in discovering as the scope of discovery is limited by the router hop count specified relative to the seed router that you choose.

1. In the Autodiscovery dialog box, ensure that the Seed Router information is correct ([Figure 4-2](#)).

The screenshot shows the 'Autodiscovery' dialog box with the 'Scheduler' tab selected. The 'IP Discovery' section is active, and the 'Router Discovery Using Routing Tables' checkbox is checked. The 'Seed Router' section contains the following fields:

Seed Router IP Address	134	177	122	1
Subnet Mask	255	255	255	0
Read Community String	public			
Hop Count	4			

There is a 'Discover' button to the right of the Hop Count field.

The 'ARP Cache' section has an 'Add Subnet Address' field with an 'Add' button. Below it are two columns: 'Available Subnets' and 'Subnets To Discover'. The 'Subnets To Discover' column has a 'Delete' button and a 'Discover' button.

The 'Range PINGing' section has 'From' and 'To' fields. The 'From' field contains '10.157.2.1' and the 'To' field contains '10.157.2.255'. There are 'Add', 'Delete', and 'Discover' buttons associated with this section.

At the bottom of the dialog box are 'OK', 'Cancel', and 'Help' buttons.

Figure 4-2. Autodiscovery Dialog Box—Seed Router Section

The Seed Router information is read only dynamically when you select the Router Discovery Using Routing Tables option. Therefore if necessary, select the Router Discovery Using Routing Tables option and type any information that you want to change.

The Discovery Seed Router is the IP address of the router that Autodiscovery uses as the seed to initiate the discovery process. This IP address is written to the *synopt.ini* configuration file. If the seed router IP address is wrong, Autodiscovery fails.

The Discovery Seed Router Community String is case sensitive.

The BootP and Trap Registration processes use the Host IP Address text box information to notify agents of the IP address of the Optivity Campus management station. The trap registration process informs agents to send their traps to the Optivity Campus management station and the BootP server process informs agents from what IP address to request TFTP agent configuration file downloads.

2. If any of the Seed Router information is incorrect, type the correct information.

Alternatively, you can use the System Properties dialog box NMS Configuration tab to specify a default router. Choose Start > Programs > Optivity > Optivity System Preferences.

Specifying Community Strings

Community strings control access to your network resources. There are two types of SNMP community strings:

- Read
- Read/write

The read community string controls which management station can read the management information base (MIB) for a particular device. The read/write community string controls which management station can have full access to (read and write) to the MIB of a device.

By default, the read community string of a device is set to “public.” The read/write community string of a device is set to “private.” This means that any management station can access information for that device.

Community strings are case sensitive.

If all of the devices on your network have the default community strings, you do not need to specify the community string names beyond the default.

If you have changed the community strings of your devices from the default settings, then you need to specify those changed community strings to match in Optivity. Otherwise, Autodiscovery will not be able to discover these devices.

In the System Properties dialog box, the Community Strings tab lets you add to or change the non-default read community strings for devices on your network. If you added non-default community strings during the installation process, they appear in the tab.

To add non-default read community strings:

1. **Choose Start > Programs > Optivity > Optivity System Preferences.**

The System Properties dialog box opens.



Note: Alternatively, you can use the Set Community Strings utility from HP OpenView. Choose Applications > Set Community Strings. See [“Specifying Community Strings” on page 4-5](#).

2. Click the Community Strings tab (Figure 4-3).




Figure 4-3. System Properties Dialog Box—Community Strings Tab

The System Defined Read Community is already displayed. It is the default read community string your management station uses to communicate with devices.

3. **In the Commonly Used Read Community Strings field, type a non-default read community strings used on your networks and subnetworks.**

Perform this step only if you use multiple read-only community strings on your Nortel Networks network devices. If the community strings are not added to the list, Nortel Networks devices cannot be discovered or polled for status.



Note: Do not add any read/write community strings. Add only applicable read community strings. Community strings are case sensitive; therefore, ensure that you type the proper case.

4. Click Add.

The community string you just typed is displayed in the list box. To delete community strings, select the community string from the list box and click Delete.

5. Click OK.

Running Autodiscovery

The first time you start Optivity Campus, the Autodiscovery dialog box is open. Subsequently use the Autodiscovery toolbar button or the Applications > Autodiscovery command to open the Autodiscovery dialog box. The Autodiscovery dialog box provides three discovery options, each on a separate tab: IP Discovery, IPX Discovery, and Scheduler.



Note: If your management station is configured for IP only, you do not see the IPX Discovery tab. If your management station is configured for IPX only, you do not see the IP Discovery tab. You see both tabs if your management station is configured for both protocols.

Autodiscovery does the following:

- Discovers all of the file and print servers in your network
- Discovers all of the Nortel Networks hubs, routers, bridges, and switches on the specified subnet
- Discovers the various LAN segments and rings in your network
- Displays the discovered devices in the appropriate Campus Command Center folder

Using IP Discovery

The IP Discovery tab in the Autodiscovery dialog box displays the three discovery methods: ARP Cache, Range PINGing, and Router Discovery. You can use one or all discovery methods. [Table 4-2](#) describes each discovery method.

Table 4-2. IP Discovery Methods

IP Discovery Method	Description
Router Discovery	Discovers routers, networks, and subnetworks. Enable the Router Discovery Using Routing Tables check box if you want Autodiscovery to discover available networks and subnetworks in your network and the routers that are connected to those networks.
ARP Cache	Uses Address Resolution Protocol (ARP) information from routers on the network to discover devices that communicated through the router and have had their address logged in the router ARP cache. ARP is a protocol for mapping an IP address to a physical machine address that is recognized in the local network.
Range PINGing	Sends an Internet Control Message Protocol (ICMP) echo request to each address in the specified range, discovering network devices that reply. In a routerless environment, Range PINGing is the only discovery that discovers devices.

Using Router Discovery

1. At the top left on the IP Discovery tab, check the Router Discovery Using Routing Tables check box ([Figure 4-4](#)).



Figure 4-4. Autodiscovery Dialog Box—IP Discovery Tab

When you select the Router Discovery Using Routing Tables option, the Seed Router area of the dialog box is enabled and you can modify the information if necessary. Additionally, the ARP cache and Range PINGing sections of the Autodiscovery dialog box are disabled.

2. If you have not already done so, ensure that the Seed Router information is correct.

The Seed Router section in Router discovery will update the *synopt.ini*, *comstr.ini* and *discover.ini* files accordingly, and therefore update the NMS Configuration tab in the System Preference dialog if you made any changes.

The Router Discovery Using Routing Tables option uses the seed router to discover all available subnets and routers in your network *only*. Router discovery queries the seed router for its next hop routing table and discovers all available networks and subnets within a specified hop count. The default hop count for IP router discovery is 4 hops. You can also modify the default hop count by changing the HopCount= parameter in the [X1tr Interface] section of the *discover.ini* file.

Discovered networks are displayed in the Available Subnets list box. If the Available Subnets list box is not populated, check the read community string of the default router. Open the Routers folder in Optivity Campus Command Center and Ping and SNMP Echo test the router. If the Ping succeeds but the Echo test fails, the most likely cause is an incorrect community string or manager entry associated with the community string if using a Nortel Networks seed router.

Router discovery discovers routers and automatically populates the Available Subnets list box on the IP Discovery tab with all of the available subnets in your network. It does not populate the Subnets to Discover list box that is necessary to discover the networking devices on your network and to fill the various device folders in Campus Command Center.

If the Available Subnets list box does not populate, check the read community string and/or Manager entry for the seed router.

As an alternative or in addition to the procedure described above, you can manually specify the subnets in your network that you want Autodiscovery to discover.

To manually specify a subnet to discover, type a subnet IP address in the Add Subnet Address Field and click Add. Repeat the process until you have added all of the subnets that you want Autodiscovery to discover.

Once you have used one of the two discovery methods described above to populate the Autodiscovery dialog box with subnets to discover, clicking Discover starts the ARP discovery process (see [page 4-13](#)).

Routers serving the specified networks are queried for the contents of their ARP cache. Those devices whose IP addresses fall within the discovery range are queried via SNMP to determine the device type. Those device that respond and are of a type that Optivity supports.

3. Click Discover.

The Autodiscovery process begins. The Autodiscovery icon turns red in the Campus Command Center toolbar. The icon turns green when the Autodiscovery process is completed. Also the Status Bar displays “Autodiscovery Not Running.” You see all of the available subnets on your network ([Figure 4-5](#)).




Figure 4-5. Autodiscovery Dialog Box—Router Discovery

Using ARP Cache Discovery

When the Router Discovery Using Routing Tables option is not selected in the Autodiscovery dialog box,

To select subnets for ARP Cache discovery:

- 1. On the Autodiscovery IP Discovery tab, deselect the Router Discovery Using Routing Tables option.**

The ARP Cache Discovery area is disabled if you have selected the Router Discovery Using Routing Tables option.



Note: This step assumes that you have run Router Discovery Using Routing Tables as described on [page 4-10](#), otherwise skip to the next step.

-
- 2. In the Available Subnets list box, select the available subnets within which you want Autodiscovery to discover your networking devices.**
 - 3. Click Add.**

The selected subnet address is listed in the Discover Subnets list box ([Figure 4-6](#)).




Figure 4-6. Autodiscovery Dialog Box—ARP Cache Discovery

To remove a subnet from the Discover Subnets list box, select the address in the list box and click Delete.

4. **Repeat steps 2 and 3 for all subnets that you want Autodiscovery to discover.**

After you run discovery once, all the discovered subnets are displayed in the All Subnets list box. If not, the read community string for the default router is probably incorrect. You can verify the default router address and community string using the Optivity System Preferences dialog box. Choose Start > Programs > Optivity > Optivity System Preferences.

If you did not run Router Discovery Using Routing Tables or wish to manually specify the range of discovery, you can manually type the subnets that you want Autodiscovery to discover.

To manually specify a subnet to discover, type a subnet IP address in the Add Subnet Address Field and click Add. Repeat the process until you have added all of the subnets that you want ARP discovery to discover.

Routers serving the specified networks are queried for the contents of their ARP cache. Those devices whose IP addresses fall within the discovery range are queried via SNMP to determine the device type. Those device that respond and are supported by Optivity Campus are added to their respective Campus Command Center folder.

To remove a subnet from the Discover Subnets list box, select a subnet and click Delete.

5. **Click Discover.**

Devices belonging to networks listed in the Discover Subnets list box are discovered by reading the ARP caches of previously discovered routers. The Autodiscovery process begins. The Autodiscovery icon turns red in the Campus Command Center toolbar. The icon turns green when the Autodiscovery process is completed. Also the Status Bar displays “Autodiscovery Not Running.”



Note: The ARP Cache discovery process is aware of routers on the network. Even if you have not run Router Discovery Using Routing Tables and Discovery is running for the first time, the ARP Discovery utility still proceeds to retrieve routing information from the seed router so that appropriate next hop routers to query can be discarded. This process will not, however, populate the Available Subnets list box in the Autodiscovery dialog box.

Using Range PINGing

Range PINGing is commonly used as an alternative discovery method to router discovery and ARP Cache discovery either to limit the scope of discovery to three very specific address ranges or as a discovery method for routerless environments.

Range PINGing involves sending an ICMP Ping to determine what IP devices are alive on the network. It then sends an SNMP request to determine device type. As with ARP Cache discovery, devices responding that are within the range of the device type that Optivity Campus has been designed to identify are discovered.

To select subnets for Range PINGing discovery:

1. **Type the starting and ending host address in the From and To text boxes** ([Figure 4-7](#)).




Figure 4-7. Autodiscovery Dialog Box—Range PINGing Discovery

2. **Click Add.**

The specified range is added to the Range PINGing range list box. To remove a subnet address range from the Range PINGing range list box, select the range you want to remove and click Delete.

3. Repeat steps 1 and 2 until you have specified all of the addresses.
4. Click Discover.

The Autodiscovery process begins.



Note: You can use the Scheduler to schedule Autodiscovery to occur later at a specified time or interval (see [page 4-18](#)).

Using IPX Discovery

IPX Discovery involves discovering the hubs from the IPX server bindery.

To use the IPX Discovery:

1. In the Autodiscovery dialog box, click the IPX Discovery tab.

The IPX Discovery tab opens ([Figure 4-8](#)). If your management station is not running IPX, this tab is not available.




Figure 4-8. Autodiscovery Dialog Box— IPX Discovery Tab

2. **Select a segment from the Available Segments list, or manually type a segment IP address using the Segment Address text box.**

3. **Click Add.**

The selected segment address is displayed in the Discover Segments list box. To remove a segment address from the Discover Segments list box, select the address you want to remove and click Delete.

4. **Repeat steps 2 and 3 until you have specified all of the address ranges.**

5. **If you want to select IP Discovery options, see [“Using IP Discovery”](#) on [page 4-9](#).**

6. **Click Discover.**



Note: You can use the Scheduler to schedule Autodiscovery to occur later at a specified time or interval. See [“Scheduling Discovery”](#) next in this chapter.

Scheduling Discovery

The Autodiscovery Scheduler lets you schedule Autodiscovery to automatically occur daily or at a specific interval.

To ensure that the Optivity database is updated with the latest network information, schedule Autodiscovery to occur on a regular basis. You can schedule Autodiscovery to occur daily at a specified time or you can schedule Autodiscovery to occur at specific time intervals. Nortel Networks recommends that you schedule Autodiscovery to occur at a time when network activity is low and when other tasks are not running on the Optivity Campus management station.

To schedule the Autodiscovery process:

1. **In Optivity Campus Command Center menu bar, choose Applications > Autodiscovery or click the Autodiscovery toolbar button.**

The Autodiscovery dialog box opens ([Figure 4-9](#)).




Figure 4-9. Autodiscovery Dialog Box—Scheduler Tab

2. **Click the Scheduler tab.**
3. **To schedule Autodiscovery daily at a specific time, check the Start Daily At check box, type the specified time in the text box, and click the AM or PM option.**

The Start Daily At Autodiscovery option is automatically checked by default.

4. **To schedule Autodiscovery to occur periodically at a specified interval, check the Start At Intervals Of check box and type the hours in the text box.**
5. **Click Discover to automatically start Autodiscovery at the specified time or interval.**

Click OK to save the information and close the Autodiscovery window. To disable Autodiscovery at a specified time or interval, deselect everything on the Scheduler tab and click OK.

Saving a Campus Command Center View

After discovered devices are displayed in the Optivity Campus Command Center, you can save the view, which results in creating a configuration file (.ccc).

A configuration file includes the following information:

- Device information for each folder, such as network address, host name, or MAC address
- Current selections in the Contents folder
- Thresholds

To save a Campus Command Center view and create a configuration file:

1. **From the Optivity Campus Command Center menu bar, choose File > Save or click the Save toolbar button.**

The Save File dialog box opens.

2. **Type a file name and click Save.**

The next time you open Campus Command Center, the last saved view is automatically loaded. The saved configuration file is displayed at the bottom of the File menu. If you try to exit the Campus Command Center without saving changes to your current configuration file, you are prompted to confirm whether or not to save your changes before you exit.



Note: To view a list of previously saved views, edit the [RecentFileList] section in the *ccc.ini* file. The file referenced by the “File1=” parameter is automatically opened the next time you start Optivity Campus Command Center.

Running Optivity Node Discovery

Node Discovery is an Optivity utility that supplements the other Optivity Discovery processes and adds additional information to the Optivity database using the Show Nodes information obtained from Nortel Networks devices. Node Discovery discovers nodes in your segment and link label information (the slots and ports through which devices are connected to other devices). Link label information is viewable in the Optivity segment view map. Node information is used for the Find Node application and other applications such as Nodal View. Run Node Discovery prior to using Optivity for the first time. Additionally, run Node Discovery periodically thereafter.



Note: For some applications, such as Nodal View, information can be discovered dynamically and added to the database on an as-needed basis. For other applications, such as Find Node, Node discovery must be run first before launching the application.

To run Node Discovery:

- **From the Campus Command Center menu bar, choose Applications > Node Discovery.**

Node Discovery starts immediately discovering nodes learned by querying devices for their Show Nodes tables. Show Nodes information is stored in the Optivity database for future use.

The Node Discovery process begins. Node Discovery may take several minutes. Node Discovery is complete when the Node Discovery window closes.

Setting Optivity System Preferences

The Optivity System Preferences let you change preferences for the Optivity Campus Command Center, Community Strings, and NMS Configuration. You can change Optivity system preferences at any time so that you do not have to reinstall the software to update the information.

Changing Campus Command Center Preferences

The Command Center tab allows you to change default information and MAC address format.

To change Command Center preferences:

1. **Choose Start > Programs > Optivity > Optivity System Preferences.**

The System Properties dialog box opens ([Figure 4-10](#)). The Command Center tab is displayed by default.




Figure 4-10. System Properties Dialog Box—Command Center Tab

2. **Type the time in seconds to wait for a response from a device.**
3. **Type the time in seconds for Optivity Campus to poll a device.**
4. **Type the number of retries for getting information from a device.**
5. **Type the time out in seconds for out-of-band operations.**

6. Select the MAC Address format type that you want.

If you select the vendor type, the MAC address is displayed in Optivity applications by vendor name followed by six hexadecimal numbers. If you select the hex type, the MAC address is displayed in Optivity applications in hexadecimal format.

7. Click Reset To Default if you want to go back to the default values.

Changing NMS Configuration

The network management station (NMS) Configuration tab allows you to change the IP address of the Optivity Campus host management station, the discovery seed router, subnet mask, and the discovery seed router community string you entered during the installation process.

To change NMS configuration:

1. Choose Start > Programs > Optivity > Optivity System Preferences.

The System Properties dialog box opens. The Command Center tab is displayed by default.

2. Click the NMS Configuration tab ([Figure 4-11](#)).




Figure 4-11. System Properties Dialog Box—NMS Configuration Tab

3. **Type the IP address of the discovery seed router in the Discovery Seed Router field. Type 1.1.1.1 for a routerless network.**
4. **Type the subnet mask of the network in the Subnet Mask field.**
5. **Type the read community string of your seed router in the Default Gateway Community String field. In a routerless environment, accept the default (public).**
6. **Type the IP address of the Optivity Campus management station.**
7. **Click OK to save the new information.**

All the information is saved in the Optivity database.

If you click Cancel, the System Properties information is not changed in the database.

Using Optivity Campus Applications

After you have a NetView or NNM map, you can use Campus Command Center and the Optivity Campus integrated applications to manage, monitor, and configure your network.

For information about using the Optivity Campus applications, see *Using Optivity Campus 7.0* (located on the Optivity Campus 7.0.2 Documentation CD), or use the Optivity Campus Online Help System.

To view the Optivity Campus Online Help System, choose Help > Optivity Index from the Campus Command Center menu bar.

To use the *Optivity Campus 7.0.2 Documentation CD*:

1. **Insert the *Optivity Campus 7.0.2 Documentation CD* in your management station CD-ROM drive.**

2. **Choose Start > Run.**

The Run dialog box opens.

3. **Type the following:**

<CDROMdrive>:\Welcome.pdf

4. **Click OK.**

The *Optivity Campus 7.0.2 Documentation CD* interface opens in Adobe Acrobat.

5. **Click Main Menu.**

The list of documentation opens.

6. **Click the document that you want.**

Symbols

.ini files, Optivity Campus, where saved during upgrade, 2-8

A

advanced agents, 1-3

Advanced Analyzer agents, 1-3

agent software, downloading, 1-3

agents

advanced, 1-3

Advanced Analyzer, 1-3

software, downloading, 1-3

standard, 1-3

supported, 1-3

applications, Optivity Campus, using, 4-24

ARP Cache IP Discovery, 4-13

defined, 4-9

audience, intended, xii

Autodiscovery, 4-3, 4-5, 4-8

description, 4-3

dialog box, 4-8

discovery seed router IP address, 4-5

flat network hellos, filtering, 1-5

host IP address, 4-5

how it works, 4-8

IP Discovery

ARP Cache, 4-9

Range PINGing, 4-9, 4-16

Router Discovery, 4-9

IP Discovery, using, 4-9

IPX Discovery, 4-17, 4-18

scheduling, 4-18

seed router, specifying, 4-11

segment hellos, filtering, 1-4

Autodiscovery dialog box

IP Discovery tab, shown, 4-10, 4-14

IPX Discovery tab, shown, 4-17

Scheduler tab, shown, 4-19

B

bridge, high speed forwarding table example, 1-5

C

Campus Command Center preferences, changing, 4-22

Communications Setup dialog box, 2-6

community string files, where saved during upgrade, 2-8

community strings

described, 4-5

discovery seed router, 4-5

non-default, adding, 4-6

specifying, 2-7, 4-5

comstr.ini file, 2-8, 4-11

configuration file (.ccc)

contents, 4-20

saving, 4-20

where saved during upgrade, 2-8

configuration files (.cfg), where saved during upgrade, 2-8

constr.ini file, 2-8

conventions, text, xii

customer support, xiv

D

- database file, backing up, 3-2
- descbd.ini file, 2-8
- device discovery, 4-3
 - ARP Cache, 4-13
 - Autodiscovery, 4-3, 4-8
 - community strings, specifying, 4-5
 - IP Discovery, 4-9
 - IPX Discovery, 4-17
 - Node Discovery, 4-3
 - nodes, 4-21
 - Range PINGing, 4-15
 - router discovery, 4-10
 - scheduling, 4-18
 - seed router
 - choosing, 4-4
 - types, 4-3
- DHCP, not supported, 2-10
- discover.ini file, 4-11
 - specifying default hop count, 4-11
- discovery seed router
 - community string, 4-5
 - IP address, 4-5
- documentation CD, using, 4-25

F

- flat network multicast address example, 1-6

G

- gateway IP address, specifying, 2-6

H

- hellos
 - flat network, filtering, 1-4, 1-5
 - segment, filtering for Autodiscovery, 1-4
- hop count, default
 - specifying for Autodiscovery, 4-11
 - specifying in discover.ini file, 4-11
- host IP address, 4-5
 - specifying during install, 2-6
 - specifying in system preferences, 4-24
- HP OpenView Network Node Manager, starting, 4-1

I

- image files, where saved during upgrade, 2-8
- installation
 - Optivity Campus, 2-2
 - post tasks, 3-1, 3-2
 - preparation, 1-1
- internetworking module requirements, 1-4
- IP address
 - changing in system preferences, 4-24
 - management station, specifying during install, 2-6
 - static, 2-10
- IP Discovery
 - ARP Cache Discovery, 4-13
 - Range PINGing, 4-9, 4-15
 - router, 4-9, 4-10
 - starting, 4-9
- IP Discovery methods
 - ARP Cache, 4-9
 - Range PINGing, 4-9
 - Router Discovery, 4-9
- IP Discovery tab, Autodiscovery dialog box (CCC), 4-9
- IPX Discovery tab, Autodiscovery dialog box (CCC), 4-17
- IPX Discovery, using, 4-17

N

- network administrator requirements, xii
- network environment for Optivity Campus, 1-2
- network information requirements, 1-6, 2-6
 - checklist, 1-7
 - community strings of devices, 1-7
 - device IP addresses, 1-6
 - management station IP address, 1-6
 - subnet mask, 1-6
- Network Management Platform Selection dialog box, shown, 2-3
- network settings, changing in Optivity Campus, 2-10
- NMS configuration preferences, changing, 4-23
- Node Discovery, 4-3, 4-21
 - description, 4-3
 - running, 4-21

O

Optivity Campus

- agents, supported, 1-3
 - audience, xii
 - communications stack, supported, 1-3
 - documentation CD, using, 4-25
 - files saved during upgrade, 2-8
 - installing, 2-2
 - network environment, 1-2
 - network information requirements, 1-6
 - Node Discovery, 4-21
 - preferences, 4-21
 - starting, 4-1
 - system requirements, 1-2
 - troubleshooting, 2-10
 - uninstalling, 2-9
 - upgrading, 2-8
- Optivity database files, where saved during upgrade, 2-8
- Optivity System Preferences dialog box
- network settings, changing, 2-10
- Optivity system preferences, setting, 4-21

P

- PATH variables, 3-1
- Ping, using to verify connectivity, 2-10
- preferences, Optivity system, setting, 4-21
- product support, xiv
- publications
- hard copy, xiv
 - related, xiii

R

- Range PINGing IP Discovery, 4-9, 4-15
- read community string
- changing in system preferences, 4-24
 - defined, 4-5
 - specifying during install, 2-6
- read/write community string, defined, 4-5
- router
- database, updating with management station IP address, 1-6
 - functioning as bridge, configuring, 1-6
 - seed, choosing, 4-4

Router Discovery

- defined, 4-9
- using, 4-10

S

- Scheduler tab, Autodiscovery dialog box (CCC), 4-19
- scheduling Autodiscovery, 4-18
- seed router
- choosing, 4-4, 4-11
 - information, verifying, 4-5
- segment multicast address example, 1-6
- Setup Components dialog box (HP OpenView NNM), shown, 2-4
- setup program
- Communications Setup dialog box, 2-6
 - default destination directories, 2-5
 - Network Management Selection dialog box, shown, 2-3
 - Optivity Campus components, 2-5
 - Optivity Campus Setup dialog box, shown, 2-4
 - running, 2-2
 - troubleshooting, 2-5
 - understanding Windows environment changes, 3-1
 - what it does, 2-2
- SNMP agents, supported by Optivity Campus, 1-3
- SNMP community strings, specifying, 1-7, 4-5
- software
- installing, 2-2
 - uninstalling, 2-9
 - upgrading, 2-8
- standard agents, 1-3
- starting
- Autodiscovery, 4-8
 - HP OpenView Network Node Manager, 4-1
 - Node Discovery, 4-21
 - Optivity Campus, 4-1
 - Tivoli TME 10 NetView, 4-1
- static IP address requirement, 2-10
- subnet mask, 1-6
- changing in system preferences, 4-24
 - specifying during install, 2-6
- support, Nortel Networks, xiv
- synopt.ini file, 2-8, 4-11
- network settings, changing, 2-10

system preferences

- Campus Command Center, 4-22
- Community Strings, 4-6
- NMS configuration, 4-23

System Properties dialog box

- Command Center tab, 4-23
- Command Center tab, shown, 4-22
- Community Strings tab, 4-8
- Community Strings tab, shown, 4-7
- NMS Configuration tab, 4-23
- NMS Configuration tab, shown, 4-23

system requirements, 1-2

T

TCP/IP stack supported, 1-3

technical publications, xiv

technical support, xiv

text conventions, xii

thldplt.ini file, 2-8

Tivoli TME 10 NetView, starting, 4-1

troubleshooting, 2-10

U

uninstalling Optivity Campus, 2-9

upgrading Optivity Campus, 2-8

- files saved, 2-8
- saved file location, 2-8

V

view, Campus Command Center, saving, 4-20

W

win.ini file, modifying after Optivity Campus
uninstall, 2-9

Windows environment changes made during install,
3-1